# Lecture 14: Color Sensing

## Yuhao Zhu

http://yuhaozhu.com yzhu@rochester.edu CSC 259/459, Fall 2025 Computer Imaging & Graphics

# The Roadmap

**Theoretical Preliminaries** 

Human Visual Systems

Display and Camera

Modeling and Rendering

Sources of Color

Display and Lighting

Photographic Optics

Image Sensor


Image Signal Processing
Image/Video Compression
Immersive Content


# Goal of Color Sensing

What if this is not true? Metamers in human vision would not be metamers in camera vision: colors appearing different to your eyes would look the same in photos and vise versa.

Sensor color

space





https://9to5mac.com/2017/12/07/iphone-flikr-most-used-camera/

https://www.eyeworld.org/research-finds-human-visual-cortex-continues-development-mid-30s

## How to Sense Color?

Principle of **univariance**: once a photon is converted to an electron, we lose wavelength/color information (there is no red electron vs. blue electron).


How do humans sensor color? We have **three** types of cones, each has a different **spectral sensitivity** to light.

• Light spectrum gets transformed to three numbers (L, M, S cone responses, or equivalently the tristimulus values in a color space).

Cameras also need to somehow generate three numbers from light too.

The three values should ideally be the same as the LMS cone responses.

• Or can be converted to tristumulus values in one of the known color spaces.




Effectively we need to have three kinds of sensors, each has a unique *spectral* sensitivity function (SSF).


SSF( $\lambda$ ): generated electrical energy per unit incident light energy at a given  $\lambda$ .



## How should SSFs look like?


- Ideally: each sensor's SSF mimics LMS and XYZ, since CMFs in other color space usually involve negative values that are physically unrealizable.
- Reality: hard to be exact. SSF depends on lots of things (sensor quantum efficiency, microlens, filters, manufacturability, etc.).







# Astrophysical Imaging Uses More Filters

Spectral transmittance of the five filters in the first SDSS camera








# Realizing "Three Kinds of Sensors"


# Take Three Separate Shots and Combine Them











1906 by Dr. Adolf Miethe



Sergey Prokudin-Gorsky (1836 — 1944)

## Use Three Sensors

#### Use three sensors

### Similar to "three shots" (previous slide)




Figure 14.3 (a) Three-sensor camera. (b) Sequential colour camera.

## Use Three Sensors

#### Use three sensors






Figure 14.3 (a) Three-sensor camera. (b) Sequential colour camera.



# Multi-Chip Sensing in Astrophysics






# Vertical Stacking

Longer-wavelength light penetrates deeper into silicon.

Sensitivity(B) = Absorption(B) Sensitivity(G) =  $Transmittance(B) \times Absorption(G)$ 


Sensitivity(R) =  $Transmittance(B) \times Transmittance(G) \times Absorption(R)$ 






# Color Filtering Array








Bryce Bayer (1929 — 2012)






# Color Filtering Array

Each filter has a unique **spectral transmittance function**, which characterizes the percentage of photons that can get through at each wavelength.



# Filters Dim Lights




$$Y_R(x,y) = \int_{\lambda} \Phi(\lambda) \; R(\lambda) \; IR(\lambda) \; M(\lambda) \; CFA_R(\lambda) d\lambda$$
 Spectral transmittance Spectral transmittance of the

of IR filter

Incident light

Microlens array Photodiode




Spectral transmittance of

red filter in the CFA

# Reading Sensor Specification: ONSemi NOII4SM6600A

#### Monochromatic sensor



#### **ELECTRO OPTICAL SPECIFICATIONS**

Parameter	Specification
FPN (local)	<0.20%, 2 LSB10
PRNU (local)	<1.5%
Conversion Gain	43 μV/e <sup>-</sup>
Output Signal Amplitude	0.6 V
Saturation Charge	21500 e <sup>-</sup>
Sensitivity (peak)	411 V.m <sup>2</sup> /W.s 4.83 V/lux.s
Sensitivity (visible)	328 V.m <sup>2</sup> /W.s 2.01 V/lux.s
Peak QE * FF Peak Spectral Response	25% 0.13 A/W
Fill Factor	35%
Dark Current	3.37 mV/s 78 e-/s
Dark Signal Non Uniformity	8.28 mV/s 191 e-/s
Temporal Noise	24 RMS e-
Signal/Noise Ratio	895:1 (40 dB)
Dynamic Range	59 dB
Spectral Sensitivity Range	400 - 1000 nm
Optical Cross Talk	15% 4%
Power Dissipation	225 mW

## Reading Sensor Specification: ONSemi KAF-8300




Figure 2. Block Diagram (Color)

**Table 6. SPECIFICATIONS** 

Description	Symbol	Min.	Nom.	Max.	Unit
ALL DEVICES					
Minimum Column	MinColumn	575	-	-	mV
Linear Saturation Signal	N <sub>e</sub> - <sub>SAT</sub>	25.5	-	-	ke⁻
Charge to Voltage Conversion	Q–V	22.5	23.0	-	μV/e⁻
Linearity Error	LeLow10 LeLow33 LeHigh	-10 -10 -10	- - -	10 10 10	%
Dark Signal (Active Area Pixels)	AA_DarkSig	-	-	200	e <sup>-</sup> /s
Dark Si <mark>(</mark>				200	e <sup>-</sup> /s
Readou Dark curre	nt halves	as the	9	15	mV/s
Flush C temperature	drops b	v 5.8°	C.	90	mV/s
Dark Si <mark>(</mark>	DSNU_Step DSNU_H	- -	0.14 0.40	3.0 0.5 1.0	mV p-p
Dark Signal Doubling Temperature	ΔΤ	_	5.8		°C
J			0.0		_
Dark Reference Difference, Active Area	DarkStep	-3.5	0.15	3.5	mV
Dark Reference Difference,	<u> </u>	-3.5 -		3.5 1.08	
Dark Reference Difference, Active Area	DarkStep	-3.5 - -			mV
Dark Reference Difference, Active Area Total Noise	DarkStep  Dfld_noi	-3.5 - - -	0.15 -		mV mV
Dark Reference Difference, Active Area  Total Noise  Total Sensor Noise	DarkStep  Dfld_noi	-3.5 - - - - 0.999990	0.15 - 16		mV mV e-rms
Dark Reference Difference, Active Area  Total Noise  Total Sensor Noise  Linear Dynamic Range  Horizontal Charge Transfer	DarkStep  Dfld_noi  N  DR	- - -	0.15 - 16 64.4		mV mV e- rms dB
Dark Reference Difference, Active Area  Total Noise  Total Sensor Noise  Linear Dynamic Range  Horizontal Charge Transfer Efficiency	DarkStep  Dfld_noi  N  DR  HCTE	- - - 0.999990	0.15 - 16 64.4 0.999995		mV  mV  e-rms  dB  %
Dark Reference Difference, Active Area  Total Noise  Total Sensor Noise  Linear Dynamic Range  Horizontal Charge Transfer Efficiency  Vertical Charge Transfer Efficiency	DarkStep  Dfld_noi  N  DR  HCTE  VCTE	- - - 0.999990 0.999997	0.15 - 16 64.4 0.999995		mV mV e-rms dB %
Dark Reference Difference, Active Area  Total Noise  Total Sensor Noise  Linear Dynamic Range  Horizontal Charge Transfer Efficiency  Vertical Charge Transfer Efficiency  Blooming Protection	DarkStep  Dfld_noi  N  DR  HCTE  VCTE  X_b	- - - 0.999990 0.999997 1,000	0.15 - 16 64.4 0.999995	1.08 - - - -	mV mV e-rms dB % % x E <sub>SAT</sub>
Dark Reference Difference, Active Area  Total Noise  Total Sensor Noise  Linear Dynamic Range  Horizontal Charge Transfer Efficiency  Vertical Charge Transfer Efficiency  Blooming Protection  Vertical Bloom on Transfer	DarkStep  Dfld_noi  N  DR  HCTE  VCTE  X_b  VBloomF	- - 0.999990 0.999997 1,000 -20	0.15 - 16 64.4 0.999995	1.08 - - - - 20	mV  mV  e-rms  dB  %  %  x E <sub>SAT</sub> mV
Dark Reference Difference, Active Area  Total Noise  Total Sensor Noise  Linear Dynamic Range  Horizontal Charge Transfer Efficiency  Vertical Charge Transfer Efficiency  Blooming Protection  Vertical Bloom on Transfer  Horizontal Crosstalk	DarkStep  Dfld_noi  N  DR  HCTE  VCTE  X_b  VBloomF  H_Xtalk	- - 0.999990 0.999997 1,000 -20 -20	0.15 - 16 64.4 0.999995	1.08  20 20	mV  mV  e <sup>-</sup> rms  dB  %  %  x E <sub>SAT</sub> mV  mV
Dark Reference Difference, Active Area  Total Noise  Total Sensor Noise  Linear Dynamic Range  Horizontal Charge Transfer Efficiency  Vertical Charge Transfer Efficiency  Blooming Protection  Vertical Bloom on Transfer  Horizontal Crosstalk  Horizontal Overclock Noise	DarkStep  Dfld_noi  N  DR  HCTE  VCTE  X_b  VBloomF  H_Xtalk  Hoclk_noi	- - - 0.999990 0.999997 1,000 -20 -20	0.15 - 16 64.4 0.999995	1.08 20 20 1.08	mV  mV  e-rms  dB  %  x E <sub>SAT</sub> mV  mV  mV
Dark Reference Difference, Active Area  Total Noise  Total Sensor Noise  Linear Dynamic Range  Horizontal Charge Transfer Efficiency  Vertical Charge Transfer Efficiency  Blooming Protection  Vertical Bloom on Transfer  Horizontal Crosstalk  Horizontal Overclock Noise  Output Amplifier Bandwidth	DarkStep  Dfld_noi  N  DR  HCTE  VCTE  X_b  VBloomF  H_Xtalk  Hoclk_noi  f_3dB	- - 0.999990 0.999997 1,000 -20 -20 0	0.15 - 16 64.4 0.999995	1.08  20 20 1.08 159	mV  mV  e-rms  dB  %  x E <sub>SAT</sub> mV  mV  MHz

# Reading Sensor Specification: ONSemi KAF-8300

The two green filters have slightly different spectral sensitivities!




Figure 7. Typical Quantum Efficiency (Color Version)

Having microlenses improves spectral sensitivities because the FF improves!




Figure 8. Typical Quantum Efficiency (All Monochrome Versions)

Wavelength (nm)

# Reading Sensor Specification: Teledyne Prime-95B

# Being a scientific image sensor, the noise performance is much better

Specifications	Camera Performance	Camera Performance		
Sensor	GPixel GSense 144 BSI CMOS Ge	GPixel GSense 144 BSI CMOS Gen IV, Grade 1 in imaging area		
Active Array Size	1200 x 1200 pixels (1.44 Megapix	1200 x 1200 pixels (1.44 Megapixel)		
Pixel Area	11μm x 11μm (121μm²)			
Sensor Area	13.2mm x 13.2mm 18.7mm diagonal			
Peak QE%	>95%			
Read Noise	1.6e- (Median) 1.8e- (RMS)			
Full-Well Capacity	80,000e- (Combined Gain) 10,000e- (High Gain)			
Dynamic Range	50,000:1 (Combined Gain)			
Bit Depth	16-bit (Combined Gain) 12-bit (High Gain)			
Readout Mode	Rolling Shutter Effective Global Shutter			
Binning	2x2 (on FPGA)			
Linearity	>99.5%			
Cooling Performance	Sensor Temperature	Dark Current		
Air Cooled	-20°C @ 25°C Ambient	0.55e-/pixel/second		
Liquid Cooled	-25°C @ 25°C Ambient	0.3e-/pixel/second		

